

# RACKCLIENT™ - MEDIA EXTENDER



## Base System Specifications:

- Video Outputs:** NVIDIA 8500GT  
 High definition up to 1080P  
 (1) DVI with HDCP, (1) HDMI w. HDCP,  
 (1) Component (1080i), S-Video,  
 Composite-outs
- Audio Outputs:** (6) mini-jack analog outputs (7.1 sound)  
 (1) Optical SPDIF, (1) Coaxial SPDIF
- Storage:** 250GB Dockable hard drive
- Disk Drives:** (1) Dual-layer DVD±RW/CD-RW burners
- CPU:** AMD 5200+ X2 Dual Core
- Memory:** 2GB DDR2 800MHz
- OS Software:** Windows Vista Home Premium
- Tuners:** None (Optional, see below)

### Features:

- RACKCLIENT is 2U tall, 20" deep
- Optional **DualHD™** (HD DVD & Blu-Ray)
- Storage drive is **Field Servicable**
- Optional card reader available

## **\*\* Upgrades \*\***

### Storage:

- Upgrade to 500GB Hard Drive
- Upgrade to 750GB Hard Drive
- Upgrade to 1.0TB Hard Drive

### TV Tuners:

- (1) Analog NTSC Tuner
- (1) Single Analog PAL Tuner
- (1) Dual PAL/NTSC/SECAM Tuner
- (1) Hybrid NTSC & ATSC Tuner  
(2 tuners on one card)
- (2) Hybrid NTSC & ATSC Tuner  
(4 tuners on two cards)

### Optical Drives:

- Blu-Ray / DVD Burner only
- DualHD™ (Blu-ray & HD DVD, 1 drive)

### Face Plate:

- Plastic Face Plate w. Aluminum Strip Insert

### Quad Core (QC) Performance:

- AMD 9550 QC CPU, DDR3 1066MHz RAM,  
& Enhanced performance motherboard

### Processor:

- 6000+ X2 Dual Core (Multi-zone)
- 6400+ X2 Dual Core (Multi-zone)
- Quad Core 9750 CPU, 1066MHz memory\*  
(requires QC Performance Upgrade)

### Memory: (improves multizone performance)

- 4GB for Dual Core @ 800MHz
- 4GB for Quad Core @ 1066MHz

### Video Card:

- No Upgrades

### Card Reader

- Multi-card reader w. USB, Firewire, &  
Mic. + Headphones I/O Audio Ports

### Software:

- Vista Ultimate (For sharing Recorded TV)
- Blu-ray playback/streaming software\*\*\*\*

NOTE: RACK system performance is only warranted with VidaBox-supplied drives. Insertion of foreign drives will void warranty.